







# Replacement Power Supplies

## Power Supply Details


Part Number	Model/Screen size	Power Type	AC In Range	Current [Standby]	Connector Type	
AVF-PSUA12V3A	MK1-3 all sizes, Series 5 16" up to March 2017 Echo	Adaptor [12V/3.5A]	90-264V 50-60Hz	0.40A	A	
AVF-PSU24V3A	Series 5 22"- 43" + 16" from April 2017	Adaptor [24V/3A]		0.40A	B	
AVF-PSU24V6A	Series 4 32"-40", Series 5 55	Adaptor [24V/6A]		0.12A	B	
AVF-PSU24V9A	65" 1080p	Adaptor [24V/9.2A]		0.12A	B	
AVF-PSUC12V5A	Series 4 10" - 26"	Adaptor [12V/5A]		0.40A	C	
AVF-PSUD12V3A	Contract board and LED lights	Adaptor [12V/3.5A]		0.40A	D	

**NOTE: AQUAVISION DOES NOT RECOMMEND THAT YOU LENGTHEN THE INTEGRAL CABLE DUE TO POTENTIAL VOLTAGE LOSS. THIS WILL INVALIDATE YOUR GUARANTEE AND POSSIBLY DAMAGE YOUR AQUAVISION.**

## Connector Details

### Type A

MK1,2,3, S5 16" & Echo Audio System:



Centre pin +

### Type B

MK3 23", S4 & S5 16"-65"



P1	P2	P3	P4
Ground	+Vcc	Ground	+Vcc
-	+	-	+

### Type C

MK4 10.4"-20":



For use with 2.5mm centre pin products.  
Centre pin +

### Type D

Contract board LED light driver



For use with 2.1mm centre pin products.  
Centre pin +



**HEAD OFFICE AND FACTORY**  
Grosvenor Business Park  
Horsfield Way, Stockport  
Cheshire, SK6 2SU  
United Kingdom  
+44 [0]161 711 1900



sales@aquavision.tv  
sales@aquavision.us

www.aquavision.tv  
www.aquavision.us