

Legacy Product IR Codes MK1-3

	10.4", 15" and 17"	23", 26", 32", 40"	23", 26", 32" USA	17BLF	23BLF
0x00	0	0	0	0	0
0x01	1	1	1	1	1
0x02	2	2	2	2	2
0x03	3	3	3	3	3
0x04	4	4	4	4	4
0x05	5	5	5	5	5
0x06	6	6	6	6	6
0x07	7	7	7	7	7
0x08	8	8	8	8	8
0x09	9	9	9	9	9
0x0A	-	* [LEFT]	* [LEFT]	-	* [LEFT]
0x0B	-	* [RIGHT]	* [RIGHT]	-	* [RIGHT]
0x0C	POWER	POWER	POWER	POWER	POWER
0x0D	MUTE	MUTE	MUTE	MUTE	MUTE
0x0E	PSM	PSM	PSM	PSM	PSM
0x0F	-	-	-	-	-
0x10	VOL+	VOL+	VOL+	VOL+	VOL+
0x11	VOL-	VOL-	VOL-	VOL-	VOL-
0x12	-	-	-	-	-
0x13	-	-	-	VIDEO	VIDEO
0x14	SCART	-	-	-	-
0x15	-	-	-	TV	TV
0x16	-	SSM	SSM	SSM	SSM
0x17	-	-	-	-	-
0x18	-	-	-	-	-
0x19	-	TV/PC	TV/PC	PC/TV	TC/PC
0x1A	VIDEO	ARC	ARC	ARC/*	ARC
0x1B	S-VIDEO	INPUT	INPUT	-	INPUT
0x1C	-	SWAP	SWAP	-	SWAP
0x1D	-	MODE	MODE	-	MODE
0x1E	ARC	PR+ [PIP]	CH+ [PIP]	-	PR+ [PIP]
0x1F	PC	PR- [PIP]	CH- [PIP]	-	PR- [PIP]
0x20	PR+	PR+	CH+	PR+	PR+
0x21	PR-	PR-	CH-	PR-	PR-
0x22	-	-	-	S-VIDEO	S-VIDEO
0x23	-	I/II	SAP	-	I/II
0x24	-	-	-	PC	PC
0x25	OK	OK	OK	OK	OK
0x26	-	SLEEP	SLEEP	-	SLEEP
0x27	-	-	-	-	-
0x28	-	-	-	-	-
0x29	SLEEP	HOLD	-	HOLD	HOLD
0x2A	TIME	TIME	-	TIME	TIME
0x2B	SIZE	Q.VIEW	Q.VIEW	SIZE	Q.VIEW
0x2C	REVEAL	REVEAL	-	SYSTEM	REVEAL
0x2D	UPDATE	UPDATE	-	UPDATE	UPDATE
0x2E	-	-	-	MIX	-

	10.4", 15" and 17"	23", 26", 32", 40"	23", 26", 32" USA	17BLF	23BLF
0x30	-	POSITION	POSITION	-	POSITION
0x31	-	-	-	-	-
0x32	SSM	YELLOW	-	LIST	YELLOW
0x33	-	-	-	-	-
0x34	-	CYAN	-	Q.VIEW	CYAN
0x35	INDEX	LIST	LIST	INDEX	LIST
0x36	GREEN [I/II]	GREEN	-	SLEEP	GREEN
0x37	-	RED	-	I/II	RED
0x38	CYAN [TV/AV]	TV/AV	TV/AV	TV/AV	TV/AV
0x39	YELLOW [Q.VIEW]	I	-	-	-
0x3A	-	PIP	PIP	-	PIP
0x3B	RED [MENU]	MENU	MENU	MENU	MENU
0x3C	TEXT/MIX	TEXT/MIX	CC	TEXT	TEXT/MIX
0x3D	-	-	-	-	-
0x3E	ON	-	-	-	-
0x3F	OFF	-	-	-	-



HEAD OFFICE AND FACTORY
 Aquavision
 Grosvenor Business Park, Horsfield Way,
 Stockport, Cheshire, SK6 2SU
 United Kingdom

 www.aquavision.tv
 sales@aquavision.tv
 +44 [0]161 711 1900

